

## [H]ardBASS HF Drivers

# 440Ti

4.5" Titanium Compression Driver with 1.75" voice coil

### Introduction:

The 440Ti is a 4.5" Compression Driver with a 1.75" Titanium voice coil. It provides exceptionally loud HF response.

### Specifications:

600W Peak Power / 130 RMS Rating (at recommended crossover)  
1.75" Titanium Voice Coil / 4.5" Overall Diameter  
22 Oz Ceramic Ferrite Magnet  
105dB SPL Sensitivity / 1.2kHz to 20kHz frequency range  
8  $\Omega$  Nominal impedance

### Special Features:

Robust 1.75" Titanium voice coil with exceptional power handling

Easy-open voice coil for user-serviceable replacement (if necessary).

**Recommended Crossover** (HPF): 2,000Hz or higher @ 12dB/Octave or greater

### Minimum Crossover (RC):

10-ohm 33W Resistor  
3.3uF 250V Capacitor  
(see circuit diagram)

2kHz @ 6dB/Oct (RC)

