

[H]ardBASS Car Amplifier

R2000.1 Monoblock

Powerful 2000W Monoblock Car Amplifier

Introduction:

The R2000.1 Monoblock is a Powerful 2000W (750RMS) amplifier made to add huge basslines to your car audio system.

Power Output:

2000W (750 RMS)

Fuse Rating:

70A (35A x 2)

Technology:

Class D / Monoblock
High-Efficiency MOSFET

Continuous Power Output (RMS) @ 14.4V:

750 RMS @ 1-ohm
550 RMS @ 2-ohm
350 RMS @ 4-ohm

Features:

Low Pass Filter @ 12dB / Oct
Subsonic Filter @ 12dB / Oct
Bass Boosts up to +12dB
Frequency Range: 7Hz to 180Hz, less than 0.1% THD

Chassis Dimensions:
210mm x 185mm x 50mm

For more information, contact your nearest **[H]ardBASS** dealer or visit us online at www.hardbass.audio

2000W

Monoblock Car Amplifier