

## [H]ardBASS Car Amplifiers

# R5000.1 / 5K Monoblock

Premium 5000W Monoblock Car Amplifier

### Introduction:

The R5000.1 is a 5000W Monoblock Car Amplifier made to deliver unrestricted BASS performance with excellent tone.

### Advanced Components

Every R3000/R5000 Car Amplifier is made using superior-grade internal components and materials in a state-of-the-art South Korean facility.  
Premium High-Definition (HD) Signal Processing built-in  
Premium high-density (7g/mm) heatsink with anodized cooling surface  
Bass Remote included

### Power Rating:

5000W Power Rating  
200A Recommended External fuse (not included)

# 5000W

5K Monoblock Amplifier

### Continuous Power Output (RMS) @ 14.4V:

900 RMS @ 4-ohm Mono  
1500 RMS @ 2-ohm Mono  
2500 RMS @ 1-ohm Mono

# HD

High-Definition

### High-Definition (HD) Signal Processing:

Built-in HD Crossover @ 12dB/Octave slope  
Low-Pass Filter (LPF) adjustable from 30Hz to 250Hz  
Subsonic filter adjustable from 10Hz to 60Hz  
Phase Shift adjustment from 0° to 180°  
Bass-Boost @ 45Hz variable from 0dB (off) to +12dB

Chassis Dimensions: 242mm x 424mm x 55mm

For more information, contact your nearest [H]ardBASS dealer or visit us online at [www.hardbass.audio](http://www.hardbass.audio)